

# Mack Torque Chart

Model	Horse Power @ RPM	Torque @ RPM
E3-190 (Mech)	190 @ 2500	475 @ 1300
E3-220 (Mech)	220 @ 2350	627 @ 1400
E6-250	250 @ 2100	750 @ 1500
E6-275	275 @ 2100	1020 @ 1200
E6-300	300 @ 1700	1112 @ 1200
E6-350	350 @ 1800	1277 @ 1250
E7-250 (Mech)	250 @ 1950	975 @ 1200
E7-300	300 @ 1800	1160 @ 1200
E7-300 (Mech)	300 @ 1950	1083 @ 1200
E7-300 (V-MAC)	300 @ 1700	1160 @ 1200
E7-310/330	310/330 @ 1800	1360 @ 1100
E7-325 VMAC	325 @ 1800	1260 @ 1250
E7-330/350	330/350 @ 1800	1460 @ 1100
E7-350	350 @ 1800	1277 @ 1250
E7-350	350 @ 1800	1360 @ 1200
E7-350 VMAC	350 @ 1800	1250 @ 1250
E7-355/380	355/380 @ 1800	1560 @ 1100
E7-375 VMAC	375 @ 1800	1460 @ 1250
E7-400	400 @ 1800	1460 @ 1250
E7-400	400 @ 1800	1460 @ 1200
E7-427	427 @ 1800	1560 @ 1250
E7-454	454 @ 1800	1560 @ 1250
E7-460	460 @ 1800	1660 @ 1200
E9	550 @ 2100	1660 @ 1300
E9-450	450 @ 1900	1495 @ 1300
E9-500	500 @ 1900	1660 @ 1300
EM6-250	250 @ 2100	940 @ 1260
EM6-250L	250 @ 1750	1190 @ 1020
EM6-275	275 @ 2100	1038 @ 1260
EM6-275L	275 @ 1750	1305 @ 1020
EM6-300L	300 @ 1750	1425 @ 1020
EM7-250 (Mech)	250 @ 1750	1190 @ 1020
EM7-250L	250 @ 1750	1190 @ 1020

Model	Horse Power @ RPM	Torque @ RPM
EM7-275	275 @ 1750	1305 @ 1020
EM7-275 (Mech)	275 @ 1750	1305 @ 1250
EM7-275 (V-MAC)	275 @ 1750	1305 @ 1250
EM7-300	300 @ 1750	1425 @ 1020
EM7-300 (Mech)	300 @ 1750	1425 @ 1020
EM7-300VMAC	300 @ 1750	1425 @ 1020